

36211-SC

AC Power PIR Motion Detector

General use PIR motion detector designed for human body detection with ambient light detection.

Power: 100 to 240VAC 50/60Hz.

Output Power: ~40W ~2A/4A surge
(SCR Output)

Photosensing Setting: =3Lux

Sensing Distance: 4-6m

Time Delay: ~40secs On Fixed

Angle Coverage: 110 °

Temperature Using: -10°C to + 45°C

Standby power consumption: <0.1W

Body Leads: ~ 1-1/4"

Pigtail Leads: Power: ~7" Line/ ~4" Load:

Mounts in 20mm Hole

DIA: 28mm (O/A) **L:** 36mm (Body) **WT:** .04



Pigtail Connector Wiring

BROWN: AC Line Input

SHORT YELLOW: Load AC Line Out

SHORT BLUE: Load Neutral

LONG BLUE: AC Neutral Line In

**NOTE: Long & Short BLUE Leads
are connected Internally**

Information including Drawings, Schematics, Links and Code (Software) Supplied or Referenced in this Document is supplied by MPJA inc. as a service to our customers and accuracy or usefulness is not guaranteed nor is it an Endorsement of any particular part, supplier or manufacturer. Use of information and suitability for any application is at users own discretion and user assumes all risk.

Information Subject to Change Without Notice
All rights are retained by the respective Owners/Author(s)



MARLIN P. JONES & ASSOC., INC.

P.O. Box 530400 Lake Park, FL 33403

800-652-6733 FAX 561-844-8764

WWW.MPJA.COM